

TECHNICAL INFORMATIONS

CHAMA / CANDLE E14

6W 3000K

Lâmpadas LED decorativas com diferentes potencias, ideais para substituir as antigas lâmpadas de vela incandescentes.

Decorative LED lamps with different wattages, ideal for replacing old incandescent candle lamps.

Bombillas LED decorativas con diferentes potencias, ideales para reemplazar lámparas de vela incandescentes.



ILAR-00413

REFERENCE

Reference	ILAR-00413
Lamp type	C37
Lamp Base	E14
Nominal Lifetime (EOL end of life)	25000h
Switching Cycle (times)	15000X
Dimmable	No
Mercury Free	Yes

DIMENSION & WEIGHT

Diameter	37mm
Length	100mm
Weight	20g

PHOTOMETRICAL DATA

Total Luminous Flux	480lm
Luminous Efficacy	69lm/W
Beam Angle	180°
Colour Temperature	3000K
Colour Rendering Index	80
Colour Consistency	<= 6

ELECTRICAL AND OPERATING DATA

Power Rated	7W
Equivalent Wattage	41W
Lamp Current	55mA
Nominal Voltage	220-240V
Operating Frequency	50/60Hz
Power Factor	0.5
Starting Time	0.5s
Warm-up Time (60%)	0.5s
Operating Temperature	-30°C to + 40°C


ENERGY LABEL & STANDARS

Energy Label	A+
Energy Consumption KWH/1000H	7kWh


CERTIFICATIONS

ROHS	YES
CE	YES
LM70	NO
LM80	YES
LM79	-
TM21	-
ENEC	-

SIZE



BEAM ANGLE



Designed by Aron Light in Portugal. Made in PRC

